

- 1 -

## IMAGE PICKUP APPARATUS

### BACKGROUND OF THE INVENTION

09943415 083101  
The present invention relates to an image pickup apparatus having a lens group including lenses movable in the optical axis direction for focusing, and  
5 an image pickup device disposed at the rear of the lens group, whereby images which are obtained by image picking-up one and the same subject on different exposure conditions and which correspond to a plurality of screens are outputted from the image pickup device,  
10 and the images are synthesized to obtain a synthesized image with a wide dynamic range. Particularly, the present invention relates to an automatic focusing (autofocus) control system in such an image pickup apparatus in which the lens group is driven to adjust  
15 the focal point in accordance with the detected levels of high-frequency components contained in the images obtained from the image pickup device.

Generally, an image pickup apparatus such as a video camera or a digital camera uses a solid-state  
20 image pickup device such as a CCD image pickup device. However, there is a problem that the dynamic range of the solid-state image pickup device is extremely narrower than that of silver haloid photographic film.

In order to solve this problem, JP-A-2000-  
25 228747 or the like proposes an image pickup apparatus

in which images that are obtained by image picking-up one and the same subject on different exposure conditions and that correspond to a plurality of screens are read out and synthesized to obtain an image  
5 that is magnified in its dynamic range and that corresponds to one screen.

That is, an image pickup apparatus is proposed such that first and second images obtained by image picking-up one and the same subject with the  
10 exposure increased and decreased respectively are acquired from a single image pickup device. Signals in areas of the second image corresponding to areas of the first image which have brightness not less than a predetermined level are substituted for the signals in  
15 the corresponding areas of the first image so as to obtain an image with a wide dynamic range.

On the other hand, most of the image pickup apparatuses such as video cameras or digital cameras, having a lens group movable in the optical axis  
20 direction for focusing have an autofocus function, and there is a great demand in such image pickup apparatuses from users. As for image pickup apparatuses having means for obtaining a wide dynamic range image, there is also a great demand in such image  
25 pickup apparatuses having an autofocus function from the users.

JP-A-63-181571, JP-A-63-125910, or the like has disclosed a method for controlling autofocus. That

09043419 083101

is, in an image pickup apparatus having a lens group which is movable in the optical axis direction to adjust a focal point, and an image pickup device which is disposed at the rear of the lens group, in the order of an increasing distance from a subject, there is proposed a method in which a high-frequency component contained in an image of the subject formed on a sensor plane of the image pickup device through the lens group is detected, and the lens group is driven by drive means in accordance with an offset from the focal point obtained from the level of the detected high-frequency component (hereinafter, referred to as "focal voltage"), so as to automatically adjust the focal point.

However, there is no description about an autofocus control method in an image pickup apparatus having means for obtaining a wide dynamic range image as described above.

#### SUMMARY OF THE INVENTION

In an image pickup apparatus which has means for synthesizing images different in exposure condition to thereby obtain an image with a wide dynamic range as disclosed in JP-A-2000-228747, and which carries out autofocus in accordance with a focal voltage detected from the image obtained from an image pickup device as disclosed in JP-A-63-181571, when the image pickup apparatus operates in a wide dynamic range mode with a

090419 08310  
FOFES0"6THE460

large difference in luminance in the screen, images corresponding to a plurality of screens obtained from the image pickup device have areas where the signal level is appropriate to the images and areas where the signal level is inappropriate to the images, that is, the signal level is saturated or the signal level is low to produce a black portion or spot.

At this time, when autofocus is carried out on the basis of only a focal voltage obtained from an image on a desired exposure condition a, out of the images corresponding to the plurality of screens, a focal voltage having a level which is large enough to detect an offset from a focal point can be detected from the area where the signal level is appropriate in the image on the exposure condition a. However, a focal voltage having a level which is large enough to detect an offset from a focal point cannot be detected from the area where the signal level is inappropriate. Therefore, focusing can be done on a subject in the area where the signal level is appropriate in the image in the exposure condition a, but focusing cannot be done on the subject in the other area.

For example, Fig. 1 shows examples of typical images obtained by image picking-up one and the same subject on different exposure conditions. As shown in Fig. 1, assume that when a person B in the bright outdoors was picked up through a door from a dark room, there were obtained a first image Ia picked up on an

09043419-083101  
TOTERO"6TH4660

5           In this case, the person A in the first image  
Ia is picked up in an appropriate signal level, but the  
person B located at the center is picked up as a white  
portion or spot, inappropriate signal level.

15           In addition, a focal voltage detection area  
is generally limited as shown in Fig. 1, in order to  
stop down the lens group for making a subject brought  
into focus. In this case, there is a problem that a  
sufficient focal voltage cannot be obtained from a  
20 focal voltage detection area in the image Ia so that a  
stable focusing operation cannot be carried out.

An object of the present invention is to provide an image pickup apparatus in which a plurality of images obtained by image picking-up one and the same subject on different exposure conditions are synthesized to obtain a wide dynamic range image, wherein the plurality of images are selectively made to be targets of autofocus control so that a stable

focusing operation can be carried out in outputting the wide dynamic range image.

To solve the foregoing problems, the present invention provides an image pickup apparatus in which one and the same subject is image picked-up on different exposure conditions and adjacently temporally to thereby generate images corresponding to a plurality of screens different in exposure condition, and the plurality of images are synthesized to generate a synthesized image with a wide dynamic range. The image pickup apparatus according to the present invention comprises means for detecting focal voltages, which are high-frequency components contained in the plurality of screens, from the respective screens, and for storing the detected focal voltages; and focal voltage selecting means for comparing the stored focal voltages, and selectively outputting one of the focal voltages as a focal voltage to be referred to by autofocus means on the basis of a predetermined selection criterion. Then, a lens group is driven in accordance with an offset from the focal point obtained from the outputted focal voltage so that automatic focusing taken on the subject in various luminance areas can be carried out.

In addition, normalization processing is carried out on each of the focal voltages detected from the plurality of screens adjacent temporally and different in exposure condition, so as to eliminate the

09043419-083101  
FOI EEO 67E4660

difference between the focal voltages caused the different exposure conditions and therefore eliminate an influence of variation in exposure condition on the focal voltages.

5           In addition, in the automatic focusing, the focal voltage outputted by the focal voltage selecting means at the time of starting to drive the lens group is kept on outputting for a period from starting of drive of the lens group to conclusion of reaching  
10 focusing to thereby stop moving the lens group.

          In addition, when the focal voltage is to be selected, the focal voltage for focusing is selectively outputted on the basis of comparison among magnitudes of the stored focal voltages inputted to the focal  
15 voltage selecting means or on the basis of luminance level frequency distributions belonging to the screens respectively associated with the focal voltages.

          In addition, the selection criterion is varied in accordance with the luminance level frequency  
20 distributions belonging to the screens respectively associated with the stored focal voltages inputted to the focal voltage selecting means. Thus, characteristics such as luminance level distribution of the subject can be taken into consideration.

25           In addition, the means for storing the focal voltages respectively detected from the plurality of screens extracts specific areas from the plurality of screens made to be targets for a focusing operation on

09440083404  
FOFEB0"6TCH660

the basis of information of luminance level  
distributions expressing features of the subject or on  
the basis of information of substitute areas or a  
synthesizing ratio at the time of synthesis, or on the  
5 basis of a combination of the information of luminance  
level distributions and the information of substitute  
areas or a synthesizing ratio. The information of  
luminance level distributions is obtained from a  
plurality of screens adjacent temporally and different  
10 in exposure condition. The information of substitute  
areas or a synthesizing ratio is obtained when the  
synthesized image is generated. Then, the means  
detects focal voltages from the extracted specific  
areas of the plurality of screens, and stores the  
15 detected focal voltages.

In addition, when there is a variation in the  
exposure condition associated with the focal voltage  
outputted from the focal voltage selecting means, an  
offset from a focus position is calculated again, and a  
20 series of control in a period from starting of drive of  
the lens group to stopping of drive of the lens group  
due to detection of the focal point is performed again.

In addition, predetermined-sized areas are  
cut out from the plurality of screens respectively.  
25 Focal voltages, which are high-frequency components  
contained in the cut-out areas, are detected. The  
detected focal voltages are stored. The stored focal  
voltages are compared, and one of the focal voltages is

09043419 083104  
T07230 64460



selected on the basis of the predetermined selection criterion, and outputted from the focal voltage selecting means. Thus, the lens group is stopped down when a subject is brought into focus.

5 BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a diagram showing examples of conventional typical images obtained when one and the same subject is picked up on different exposure conditions;

10 Fig. 2 is a block diagram showing the configuration of an image pickup apparatus according to an embodiment of the present invention;

Fig. 3 is a block diagram showing the internal configuration of a focal voltage normalizing  
15 portion according to an embodiment of the present invention;

Fig. 4 is a block diagram showing another form of the focal voltage normalizing portion according to a second embodiment of the image pickup apparatus  
20 according to an embodiment of the present invention;

Fig. 5 is a flow chart showing the operation of a focal voltage selecting portion according to an embodiment of the present invention;

Fig. 6 is a graph showing a selection  
25 criterion for a focal voltage rate according to an embodiment of the present invention;

Fig. 7 is a graph showing a selection

FOFB0"6TH660

criterion for a luminance level frequency according to an embodiment of the present invention;

Fig. 8 is a graph showing variations in values of selection criteria in accordance with a focal voltage rate and a luminance level frequency according to an embodiment of the present invention; and

Fig. 9 is a flow chart showing a part of the operation of the focal voltage selecting portion according to an embodiment of the present invention.

10

#### DESCRIPTION OF THE EMBODIMENTS

A mode for carrying out the present invention will be described below with reference to the drawings.

Fig. 2 is a block diagram showing the basic configuration of an image pickup apparatus having an autofocus function according to the present invention. In the image pickup apparatus, images of two screens obtained by image picking-up one and the same subject on different exposure conditions are synthesized to obtain an image with a wide dynamic range.

This image pickup apparatus has a lens group 201, an diaphragm mechanism 202, an image pickup device 203, an amplifier 204, an A/D converter 205, a light quantity detection portion 206, a light quantity adjustment portion 207, a driver 208, a diaphragm drive portion 209, a switch 210, image data buffers 211 and 212, a synthesized image generation portion 213, an image processing portion 214, a focal voltage detecting

094419-03404

portion 215, a switch 216, a focal voltage normalizing  
portion 217, storage devices 218 and 219, a focal  
voltage selecting portion 220, an AF control portion  
221, a driver 222, and a drive portion 223. The lens  
5 group 201 is constituted by a plurality of lenses  
including lenses movable in the optical axis direction  
for focusing. The diaphragm mechanism 202 limits the  
pass quantity of luminous flux passing through the lens  
group 201. The image pickup device 203 is constituted  
10 by a color CCD or the like having an electronic shutter  
function. The amplifier 204 amplifies a signal  
component in an image signal outputted from the image  
pickup device 203 while it eliminates a noise component  
in the image signal. The A/D converter 205 converts  
15 the analog image signal amplified by the amplifier 204  
into a digital image. The light quantity detection  
portion 206 detects luminance information such as a  
light quantity or a luminance level frequency  
distribution showing the luminance level of the image  
20 digitized by the A/D converter 205. The light quantity  
adjustment portion 207 adjusts the aperture of the  
diaphragm mechanism 202, the light quantity storage  
time of the image pickup device 203, and the gain of  
the amplifier 204 to obtain images of two screens which  
25 are adjacent temporally and which are picked up on a  
high-gain exposure condition ME and in a low-gain  
exposure condition LE obtained from the detection  
result of the light quantity detection portion 206 by

09043419 083101  
"07E80"

well-known means respectively. Thus, a wide dynamic range image is generated from the images of two screens obtained by image picking-up one and the same subject on different exposure conditions. The diaphragm drive portion 209 is a motor or the like for changing the aperture of the diaphragm mechanism 202. The driver 208 controls the diaphragm drive portion 209 in accordance with an instruction from the light quantity adjustment portion 207. The switch 210 switches the destination of its output in accordance with an image switching control signal from the light quantity adjustment portion 207. The image switching control signal shows whether the image from the A/D converter 205 is the image based on the exposure condition ME or the image based on the exposure condition LE. The image data buffer 211 stores image data corresponding to one of the two screens when the output of the switch 210 is associated with the exposure condition LE. The image data buffer 212 stores image data corresponding to the other of the two screens when the output of the switch 210 is associated with the exposure condition ME. The synthesized image generation portion 213 synthesizes the data stored in the image data buffer 211 and the data stored in the image data buffer 212 by well-known means so as to generate an image corresponding to one screen with a wide dynamic range. The image processing portion 214 applies various image processing such as white balance adjustment or gamma

09043419 083404  
T07E89 6T4E4650

correction to the image obtained from the synthesized image generation portion 213. The focal voltage detecting portion 215 outputs a focal voltage showing the detection level of a high-frequency component contained in the image from the A/D converter 205. The switch 216 switches the output destination of the focal voltage detected by the focal voltage detecting portion 215, in accordance with the above-mentioned image switching control signal from the light quantity adjustment portion 207. When the output from the switch 216 is a focal voltage  $v_f\text{-LEa}$  associated with the exposure condition LE, the focal voltage normalizing portion 217 acquires a light quantity  $G_{me}$  based on the exposure condition ME and a light quantity  $G_{le}$  based on the exposure condition LE, which are supplied from the light quantity detection portion 206. Then, the focal voltage normalizing portion 217 multiplies the focal voltage  $v_f\text{-LEa}$  by a normalized coefficient obtained from the light quantities  $G_{le}$  and  $G_{me}$ . The storage device 218 stores a focal voltage  $v_f\text{-LEb}$  which has been normalized by the focal voltage normalizing portion 217. When the output from the switch 216 is a focal voltage  $v_f\text{-ME}$  associated with the exposure condition ME, the storage device 219 stores the focal voltage  $v_f\text{-ME}$ . The focal voltage selecting portion 220 compares the data stored in the storage device 218 with the data stored in the storage device 219, and selects a focal voltage for use in AF

(autofocus) control. The AF control portion 221 calculates the moving distance of the lens group 201 in accordance with a focal offset obtained from the focal voltage outputted by the focal voltage selecting

5 portion 220. The drive portion 223 is constituted by a motor or the like for moving the lens group 201 in the optical axis direction. The driver 222 controls the drive portion 223 in accordance with an instruction from the AF control portion 221.

10 Fig. 3 is a block diagram showing the processing configuration of the focal voltage normalizing portion 217 according to an embodiment of the present invention. In the focal voltage normalizing portion 217, the focal voltage  $v_f$ -LEa is  
15 normalized to eliminate a difference between the focal voltages  $v_f$ -ME and  $v_f$ -LEa caused by a difference  $G_{df}$  between the light quantity  $G_{me}$  [dB] on the exposure condition ME and the light quantity  $G_{le}$  [dB] on the exposure condition LE. An operational expression for  
20 the normalization is shown in Expression 1.

$$v_f - LEb = 10^{\left(\frac{G_{me} - G_{le}}{20}\right)} \cdot v_f - LEa \quad \text{--- Expression 1}$$

Next, the operation of the focal voltage normalizing portion 217 will be described with reference to Fig. 3. The focal voltage normalizing portion 217 receives the light quantity  $G_{le}$  detected on  
25 the exposure condition LE and the light quantity  $G_{me}$

00943419 083101

detected on the exposure condition ME, while the light quantities Gle and Gme are outputted from the light quantity detection portion 206. Then, in a subtracter 301, an operation shown in Expression 2 is performed to  
5 calculate the light quantity difference Gdf. Next, in a normalized coefficient calculation portion 302, the light quantity difference Gdf which is a decibel value is converted into a magnification value in accordance with Expression 3. Thus, a normalized coefficient Cvf  
10 for normalizing the focal voltage vf-Lea is obtained. Then, in a multiplier 303, the focal voltage vf-LEa which is the output of the switch 216 is multiplied by the normalized coefficient Cvf obtained from the normalized coefficient calculation portion 302. Thus,  
15 a focal voltage vf-LEa is normalized to obtain a focal voltage vf-LEb from which the difference between the focal voltage vf-LEa and the focal voltage vf-ME due to the difference in exposure condition has been eliminated. The focal voltage vf-LEb is set as the  
20 output of the focal voltage normalizing portion 217.

$$Gdf = Gme - Gle \quad \text{--- Expression 2}$$

$$Cvf = 10^{\frac{Gdf}{20}} \quad \text{--- Expression 3}$$

Thus, by normalizing the focal voltage vf-LEa, the focal voltage selecting portion 220 disposed in a post-stage can obtain a stable processing result

0044349.083404

independently of the variation in exposure condition.

Further, normalization processing is applied only to the focal voltage  $v_f$ -LEa associated with the exposure condition LE in the embodiment of Fig. 2.

- 5 However, as shown in Fig. 4 which is a block diagram showing a focal voltage normalizing portion of the image pickup apparatus according to a second embodiment of the present invention, focal voltage normalizing portions 401 and 402 may be provided to normalize,
- 10 respectively, the focal voltages  $v_f$ -LEa and  $v_f$ -ME supplied from the switch 216. In the configuration of Fig. 4, the focal voltage normalizing portion 401 acquires from the light quantity detection portion 206 the light quantity  $G_{le}$  based on the exposure condition
- 15 LE. Then, the focal voltage normalizing portion 401 applies an operation shown in Expression 4 to the focal voltage  $v_f$ -LEa from the switch 216 in the same processing as that in the above-mentioned focal voltage normalizing portion 217. "Go" in Expression 4
- 20 designates a desired value determined in advance, showing a reference of normalization. On the other hand, the focal voltage normalizing portion 402 acquires from the light quantity detection portion 206 the light quantity  $G_{me}$  based on the exposure condition
- 25 ME. Then, the focal voltage normalizing portion 402 applies an operation shown in Expression 5 to the focal voltage  $v_f$ -ME from the switch 216 in the same manner as that described in the focal voltage normalizing portion

09043419-033101



401.

$$vf - LEB = 10^{\left(\frac{Go - Gle}{20}\right)} \cdot vf - LEa \quad \text{--- Expression 4}$$

$$vf - MEB = 10^{\left(\frac{Go - Gme}{20}\right)} \cdot vf - ME \quad \text{--- Expression 5}$$

Thus, the focal voltages  $vf-MEb$  and  $vf-LEb$  normalized with the reference  $Go$  are always calculated. Thus, a stable focal voltage can be obtained

- 5 independently of the exposure conditions, and further, a stable operation can be obtained in the focal voltage selecting portion 220 and the AF control portion 221 disposed in a post-stage.

- Of course, the normalization operations  
10 carried out in the focal voltage normalizing portions 401 and 402 are not limited to Expressions 4 and 5. For example, a focal voltage  $vf-LEap$  associated with the exposure condition  $LE$  and a focal voltage  $vf-MEp$  associated with the exposure condition  $ME$  may be  
15 normalized in accordance with operations shown in Expression 6, as references for normalization while the focal voltage  $vf-LEap$  and the focal voltage  $vf-MEp$  are supplied from the switch 216 in a previous exposure cycle.

$$\left. \begin{aligned} vf - LEB &= \left( \frac{vf - LEa - vf - LEap}{vf - LEap} \right) \\ vf - MEB &= \left( \frac{vf - ME - vf - MEp}{vf - MEp} \right) \end{aligned} \right\} \quad \text{--- Expression 6}$$

0904349-083101

Next, the operation of the focal voltage selecting portion 220 will be described. The operation of the focal voltage selecting portion 220 is shown in the flow chart of Fig. 5. In addition, Fig. 6 is a graph showing a selection criterion for a focal voltage according to an embodiment of the present invention. The focal voltage selecting portion 220 starts selection processing of a focal voltage in synchronism with a pickup cycle on the exposure conditions ME and LE.

When the focal voltage selection processing is started, the focal voltages vf-ME and vf-LEb stored in the storage devices 218 and 219 are acquired, and the focal voltage vf-ME is divided by the focal voltage vf-LEb so as to calculate a ratio VFc (Step S1). The ratio VFc is compared with a predetermined selection reference value THm. If the ratio VFc is larger than the selection reference value THm, a value VFm indicating that the focal voltage vf-ME is selected is set in a binary flag Fsl which indicates a selected focal voltage (Steps S2 and S3). If the ratio VFc is not larger than the selection reference value THm, the ratio VFc is compared with a predetermined selection reference value THl. If the ratio VFc is smaller than the selection reference value THl, a value VF1 indicating that the focal voltage vf-LE is selected is set in the binary flag Fsl. If the ratio VFc is not smaller than the selection reference value THl ( $THl \leq VFc$ )

094419-083101  
FOIEBO"6T4E450

≤THm), the flag Fsl is not updated and the previously selected result is maintained (Steps S4 and S5). Next, with reference to the flag Fsl, the focal voltage vf-ME is outputted if the value of the flag Fsl is VFm. If  
5 the flag Fsl takes a value other than vf-ME, the focal voltage vf-LEb is outputted (Steps S6, S7 and S8). Then, the operation is terminated.

In addition, in the operation of Fig. 5, the ratio of the focal voltage vf-ME to the focal voltage  
10 vf-LEb is set to VFc. However, the result of subtraction of the focal voltage vf-LEb from the focal voltage vf-ME may be set to VFc.

Thus, a larger focal voltage is selected from the focal voltages vf-LEb and vf-ME respectively  
15 associated with the exposure conditions LE and ME, and the selected focal voltage is supplied to the AF control portion 221. As a result, a focal point which could not be detected only from a focal point associated with one of the exposure conditions LE and  
20 ME can be detected so that a stable focusing operation can be obtained independently of the luminance distribution of the subject.

In addition, a luminance level frequency distribution of an image associated with the exposure  
25 condition ME may be acquired from the light quantity detection portion 206. In this case, a luminance level frequency Ym not lower than a desired luminance level Y determined in advance is detected. The luminance level

00043419-083101  
TOTAL 6TH 60

frequency  $Y_m$  is compared with predetermined selection reference values  $Y_{TH1}$  and  $Y_{THm}$  ( $Y_{TH1} > Y_{THm}$ ), and a focal voltage may be selected in accordance with the graph of Fig. 7 which shows a selection criterion for the

5 luminance level frequency  $Y_m$ . Thus, a focal voltage is selected in accordance with the luminance level frequency distribution in the image associated with the exposure condition ME so that a subject in areas having a dominant luminance level can be selectively brought

10 into focus.

Further, processing for calculating the luminance level frequency  $Y_m$ , and processing for dynamically varying the selection reference values  $Y_{THm}$  and  $Y_{TH1}$ , for example, in accordance with the

15 characteristic shown in Fig. 8 which is a graph showing variations of the selection reference values in accordance with the focal voltage ratio  $V_{Fc}$  and the luminance level frequency  $Y_m$ , may be added to the above-mentioned processing of Fig. 5. If the selection

20 reference values  $Y_{THm}$  and  $Y_{TH1}$  are varied in accordance with the characteristic of Fig. 8, a subject located in a low-luminance area becomes easily brought into focus when the focal voltage  $v_f$ -ME of an image associated with the exposure condition ME exhibits a larger value

25 even if a high-luminance area is dominant. On the contrary, a subject located in the high-luminance area becomes easily brought into focus when the focal voltage  $v_f$ -LEb of an image associated with the exposure

09043419 083404  
FOI890 6TH660

5 existence of the subject into consideration.

YTH1 and YTHm shown in Fig. 8 may vary in curves.

15 limited.

the focal point by the AF control portion 221.

Therefore, the focal voltage selecting portion 220 always keeps on outputting a focal voltage associated with the same exposure condition in such a period.

Further, in the configuration of Fig. 2, a  
5 signal VFch indicating that a focal voltage on an exposure condition different from that for a previous focal voltage has been selected in the focal voltage selecting portion 220 may be supplied from the focal voltage selecting portion 220 to the AF control portion  
10 221. Then, when the signal VFch is detected in the AF control portion 221, an offset from a focal point is calculated again, and focus control is restarted. Thus, in such a manner that the focal voltage selecting portion 220 and the AF control portion 221 are  
15 synchronized with each other, it is possible to carry out a more stable focusing operation.

According to the present invention, there is obtained an effect that, in an image pickup apparatus in which a plurality of images of one and the same  
20 subject picked up on different exposure conditions are synthesized to obtain a wide dynamic range image, the plurality of images are selectively made to be targets of autofocus control so that a stable focusing operation can be always carried out while the wide  
25 dynamic range image is outputted.

In addition, focal voltages obtained from the plurality of images are normalized so that a stable focusing operation can be carried out independently of

00943419.03101  
F07E30" STEH660

exposure conditions.

In addition, the images made to be the targets for autofocus control are selected in accordance with luminance distribution states of picked-up images and focal voltages detected from the plurality of images. Thus, autofocus control to which the luminance distribution state of the screen and the optimum of the targets to be brought into focus are added are performed. Accordingly, a focusing operation intended by a user can be obtained.

00043419 083101  
T07E80" 6TH660